



---

# Starter

## Description

---

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.  
Characteristics: choice of normal charge, quick charge (BOOST), quick start \* timer for quick charge\* remote control \* display of charging and starting current \* protection against overloads and polarity reversal.

## Extra information

Item number	T829008	
Model	ENERGY 1000 START 230-400V	
Model group	ENERGY 1000 START 230-400V	
EAN	8004897365398	
CBS Statistics number	85044055	
Article group	Products still to be classified	
Brand	TELWIN	
Features	Mains voltage	230-400 V
	Load voltage/start voltage	12-24 V
	Loading capacity	2,5 kW
	Starting power	20 kW
	Charge current	100 A
	Rated charge current	80 A
	Starting current	640 A
	Starting peak current	1000 A
	Rated reference capacity min/max	20/1200(12V) - 20/800(24V) Ah
	Absorbed power charging/start	2,5/20 kW
	Control modes	5
Dimensions l x b x h	380 x 560 x 885 mm	
Weight	45 kg	
Article group code	485786	



